



IT-7211-PC

10/100M Ethernet to E1 Bridge User Manual

Introduction:

IT-7211-PC bridge provides easy conversion from ITU-T G.703 E1 channel to Ethernet interface. Can be used widely in connecting between WAN and LAN, monitoring, etc. The Ethernet interface is 10/100Mbps auto negotiation and can be full/half duplex. The E1 is transparent and in full rate, which can support the E1 unframed mode, including fractional E1 per request. A pair of IT-7211-PC offer a cost effective solution for using existing E1 leased lines for transparent Ethernet service. Local management of the IT-7211-PC Converter is provided via DIP switches. Front panel LEDs monitor the G.703 link, Ethernet LAN and serial ports for status and Loss of Sync. IT-7211-PC compact G.703 Access Converter provides E1/2.048 Mbps Network Termination as well as serial or Ethernet LAN interface conversion in a standalone or rack mount package. IT-7211-PC terminates the G.703 Telco interface and converts the data for transmission to a user-oriented 10/100BaseT(x) interface.

Packing List:

IT-7211-PC is shipped with following items.

1. IT-7211-PC ×1
2. 220V power line ×1
3. User manual ×1

Features:

1. Using E1 line transparent transfer Ethernet data
2. Support local clock and line clock
3. Support pretend random coding loop test

4. E1 (G.703) interface support 120ohm (RJ-45) and 75ohm (BNC double coaxial)
5. Ethernet MAC address percolate function
6. Support VLAN over length data bag
7. Ethernet port support 10M/100M full-duplex/half-duplex

Description on Installation and Panels:

1. The product front panel sketch map:



LED Indicator define:

PWR Power indicator. Brightness if electrify.

LINK Ethernet connection constitute.

_F/H Ethernet Full/half duplex indicator, bright as full duplex.

100M Ethernet port 100M indication.


10M Ethernet port 10M indication.

LOS E1 line cut alarm indicator light

TEST 7211 test state indication.

PTOK Fake random test succeed indication.

2. The product back panel sketch map:



POWER -48VDC/220VAC input choice

ON/OFF power switch


Rx/75 ohm E1-75Ω input

Tx/75 ohm E1-75Ω output

10/100M Ethernet interface (input and output)

Definition of balanced Twisted Pair(120 ohm) wire sequence for E1 and Ethernet interface:

1. Ethernet RJ-45 interface define



NO.	Function define	I/O
1	TX+ (send data +)	output
2	TX- (send data -)	output
3	RX+(receive data +)	input
4	NC(null)	
5	NC(null)	
6	RX-(receive data -)	input
7、8	NC(null)	

2. E1 interface 120 Ω /RJ-45 define

NO.	Function define	I/O
1	NC(null)	
2	RX+(receive data +)	input
3	RX-(receive data -)	input
4	GND(ground)	
5	GND(ground)	
6	TX+(send data +)	output
7	TX-(send data -)	output
8	NC(null)	

DIP switch setup:

1. Function setup switch SW1

Impedance setup

NO.1	NO.2	NO.3
ON	ON	ON: 75 ohm
OFF	OFF	OFF: 120 ohm

Ethernet working mode setup

NO.4	NO.5	NO.6	Ethernet mode
OFF	OFF	OFF	10M/100M, Fall/half duplex
OFF	OFF	ON	10M/100M half duplex
OFF	ON	OFF	Fall/half duplex 10M
OFF	ON	ON	10M, half duplex
ON	OFF	OFF	100M, full duplex
ON	OFF	ON	100M, half duplex
ON	ON	OFF	10M, full duplex
ON	ON	ON	10M, half duplex

Timepiece setup

NO.7	NO.8
ON	OFF : Inside timepiece (adopt timepiece from 7211 panel)
OFF	OFF : Resume timepiece (adopt timepiece from E1 port)

2. Function switch setup SW2

NO.1	ANA local simulation loop setup switch
NO.2	DIG local numeric loop setup switch
NO.3	Reserve
NO.4	PATT fake random test switch

SW2 switch is used, TEST indicator light is bright. Fake random test succeed, PTOK indicator light is bright.

Specifications:

E1 interface

Standard: Comply with ITU-T G.703

Output tingle displace: accord ITU-TG.735 advice

Input tingle limit: accord ITU-TG.823 advice

Output tingle: accord ITU-T G.823 advice

Frame format: unframed

Interface rate: 2.048Mbps

CRC checkout: no

Port coding: HDB3

Port transmission: 2KM

Port protection: 1500V electromagnetism isolate

Port connector: 120 Ohm (RJ-45) and 75 ohm (BNC double coaxial)

Ethernet port

Interface Types: 10/100BaseT, full/half duplex

Standards Compliance: IEEE 802.3

Bit Rate: 10/100BaseT limited to Max 2.048 Mbps

Connectors: RJ45 (10/100 Base-T Electrical)

Line code: Manchester Encoding

Internal and recover clock

Environment, Power and Dimension

Working temperature: -25 to 70°C

Storage temperature: -40 to 85°C

Humidity: Relative humidity 5% to 95%

Input power: 220VAC or -48VDC

Consumption: 2W

Power protection: From high voltage/short circuit

L×W×H: 227.4mm×146.3mm×42.7mm

Shell: Plastic

Weight: 260g

Warranty: 3 years

Certifications:



Intellisystem Technologies S.r.l.

Via Augusto Murri, 1 - 96100 Siracusa

Phone +39 (0)931-1756256 / +39 (0)2-87167549 - Mobile (+39) 335 1880035
em@il: info@intellisystem.it WEB: <http://www.intellisystem.it>